

CommScope Infrastructure Academy offers installation training.

Universal Snapstak Hangers
Bulletin 7722311 Rev. D | Page 1 of 1

1

flex section
fingers

Position hanger onto the cable. Ensure four fingers of the flex section are on the cable. **NOTE: Make sure cable is straight.**

2

front latches

The installer might need to push the hanger onto the cable (away from the open end), to facilitate closing the front latches.

3

PROPERLY ALIGNED. Cable is centered within the round hanger body for easy squeezing.

4

The front latches of the hanger should be squeezed to fit into the 3/4" hole.

5

Insert front latches into the 3/4" hole and release.

| Part Number | Cable Diameter Range (mm) | Maximum stack height per cable type | | | |
|-------------|---------------------------|-------------------------------------|-------|-------|--------|
| | | Coax | Fiber | Power | Hybrid |
| SSH-M | 14 to 25 | 3 | 2 | 2 | 2 |
| SSH-L | 25 to 36 | 2 | 2 | 2 | 2 |
| SSH-XL | 36 to 51 | 2 | 2 | 2 | 2 |

Note: Add SnapStak reinforcement bar part number SSH-DB to increase stack height.

NOTE: Please ensure that all four fingers of flex section are firmly placed on the cable jacket after installation. Adjust cable in hanger to make sure it is positioned properly.

CommScope
1100 CommScope Place SE P.O. Box 339, Hickory, NC 28603-0339
(828) 324-2200 (800) 982-1708
www.commscope.com/andrew

Customer Service 24 hours
North America: +1-800-255-1479 (toll free)
Any country: +1-779-435-6500
email: acicustomersupportcenter@commscope.com

Notice: CommScope disclaims any liability or responsibility for the results of improper or unsafe installation, inspection, maintenance, or removal practices.
Aviso: CommScope no acepta ninguna obligación ni responsabilidad como resultado de prácticas incorrectas o peligrosas de instalación, inspección, mantenimiento o retiro.
Avis: CommScope décline toute responsabilité pour les conséquences de procédures d'installation, d'inspection, d'entretien ou de retrait incorrectes ou dangereuses.
Hinweis: CommScope lehnt jede Haftung oder Verantwortung für Schäden ab, die aufgrund unsachgemäßer Installation, Überprüfung, Wartung oder Demontage auftreten.
Atenção: A CommScope abdica do direito de toda responsabilidade pelos resultados de práticas inadequadas e sem segurança de instalação, inspeção, manutenção ou remoção.
Avvertenza: CommScope declina eventuali responsabilità derivanti dall'esecuzione di procedure di installazione, ispezione, manutenzione e smontaggio improprie o poco sicure.
注意: CommScope 公司申明對於於不恰當或不安全的安裝、檢驗、維修或拆卸操作所導致的後果不負責任 何義務和責任